

## Inline blade fuse holders provide a wide variety of circuit protection options

## **Product description:**

The Eaton Bussmann® series of inline and Add-A-Fuse blade fuse holders and taps meet a variety of automotive and marine circuit protection needs.

Easily applied for adding circuits to power accessories, inline blade fuse holders are available up to 60 amps.

Bussmann series inline blade fuse holders are available for the new, micro ATR blade fuses, compact ATM and low-profile ATM fuses, popular ATC fuses and, for high power needs, MAX fuses.

Package options include traditional, retail and bulk packs.

## Features and benefits:



 Now available for ATR micro fuses, conventional holders meet basic needs for circuit protection. Available ATR, ATM, ATC and MAX fuses.



 easyID™ holders indicate a blown fuse. Available for ATM, ATC and MAX fuses.



 Gasket-sealed holders seal out contaminants. Available for ATM and ATC fuses and are ideal for trailers and marine applications where water infiltration is a problem.



 Add-a-fuse holders plug into fuse blocks to create a new, fused circuit for auxiliary and accessory loads. Available for the new ATR micro fuses, ATM and low-profile ATM and ATC fuses.



Inline holders are available for ATR, ATM, ATC and MAX blade fuses




## Eaton Bussmann series inline blade fuse holders are available in a variety of styles and ratings to meet your customer's circuit protection needs.

	Traditional			Max	Wire gauge/	Lead	
Fuse	pack	Retail pack	Bulk pack (Qty)	amps	length	color	Description
Conventional							
ATR	HH2		BK/HH2 (500)	15A	#16/2X4"	Red	Holder with cover
ATM Low-profile	HHV	BP/HHV-RP	_	20A	#12/2X4"	Red	Holder with cover
ATM	HHL	BP/HHL-RP	BK/HHL (100)*	20A	#16/2X4"	Black	Holder with cover
	ННМ	BP/HHM-RP	_	30A	#12/2X4"	Red	Holder with cover
ATC	HHC	BP/HHC-RP	BK/HHC (600)	20A	#16/2X4"	Yellow	Holder without cover
	HHD	BP/HHD-RP	BK/HHD (600)	30A	#12/2X4"	Yellow	Heavy-duty fuse holder without cover
	HHF	BP/HHF-RP	_	20A	#16/2X4"	Yellow	Holder with protective cover
	HHG	BP/HHG-RP	BK/HHG (600)	30A	#12/2X4"	Yellow	Heavy-duty holder with cover
	_	BP/HHS-RP	_	20A	N/A	Blue	Self-stripping fuse holder for #18 to #14 wire
MAX	ННХ	_	BK/HHX (100)	60A	#6/2X5"	Red	Fuse holder with cover
easyID indica	ting holders w	ith open fuse illumin	ating LED				
ATM	ATM-FHID	BP/ATM-FHID	_	20A	#16/2X4"	Red	Holder with protective cover
ATC	ATC-FHID	BP/ATC-FHID	_	20A	#16/2X6"	Red	Holder with protective cover
MAX	MAX-FHID	_	BK/MAX-FHID (100)	60A	#6/2X5"	Red	Holder with protective cover
Gasket-sealed	l holders						
ATM	HHU	BP/HHU	_	30A	#12/2X4"	Red	Water-resistant holder
ATC	HHR	BP/HHR	_	30A	#12/2X5"	Red	Water-resistant holder
Add-a-fuse ho	lders — add a	10A max fused circu	iit by inserting into an ex	cisting fu	se block, mair	fuse 30A	max - fuses not included
ATR	HHTR	BP/HHTR-RP	BK/HHTR (500)	10A	#16/5"	Red	ATR 2-leg micro fuse
ATMLP	HHLP	BP/HHLP-RP	BK/HHLP (500)	10A	#16/5"	Red	Low-profile ATM fuse
ATM	ННН	BP/HHH-RP	BK/HHH (500)	10A	#16/5"	Red	ATM fuse
ATC	ННА	BP/HHA-RP	BK/HHA (500)	10A	#16/5"	Red	ATC fuse
Fuse taps — t	ap into existin	g fuse by fitting over	the fuse terminal to prov	ride a no	n-fused circuit		
ATM		BP/ATM-TAP-RP	BK/ATM-TAP (1000)	N/A	N/A	N/A	5-count pack, taps come with quick-connect crimp-on terminals
ATC		BP/ATC-TAP-RP	BK/ATC-TAP (1000)	N/A	N/A	N/A	5-count pack, taps come with quick-connect crimp-on terminals

<sup>\*</sup> Please note that BK/HHL-R does not have a cover















1000 Eaton Boulevard Cleveland, OH 44122 United States Eaton.com

Bussmann Division 114 Old State Road Ellisville, MO 63021 United States Eaton.com/bussmannseries

© 2024 Eaton All Rights Reserved Printed in USA Publication No. 10484 June 2024

Eaton, Bussmann and *easy*ID are valuable trademarks of Eaton in the US and other countries. You are not permitted to use the Eaton trademarks without prior written consent of Eaton. For Eaton's Bussmann series product information, call 1-855-287-7626 or visit: Eaton.com/bussmannseries

Follow us on social media to get the latest product and support information.











